

We Claim:

1. A Planar inverted-F Antenna (PIFA) comprising:
a top plate, a ground plane, a dielectric material
between the top plate and the ground plane, and a feed pin
5 connected to the top plate;
a first shorting pin and a second shorting pin,
the first and second shorting pins connecting the top plate
to the ground plane and being located at distances p_1 and p_2 ,
respectively, from the feed pin to provide a desired
10 impedance of the PIFA at the feed pin.
2. The PIFA of claim 1, wherein the feed pin is
connected to a transmission line, the transmission line
being used for fine-tuning of the PIFA.
15
3. The PIFA of claim 1, wherein the transmission line
is connected to a power amplifier.
4. The PIFA of claim 1 whereby a power amplifier is
20 connected to the feed pin.
5. The PIFA of claim 4, wherein the power amplifier
is a broadband power amplifier.
- 25 6. The PIFA of claim 1, wherein p_1 and p_2 are
substantially equal.
7. The PIFA of claim 1, wherein the top plate is
rectangular.
30

8. The PIFA of claim 1, wherein an imaginary line between the feed pin and the shorting pins forms substantially a right angle.

5 9. The PIFA of claim 1, wherein the dielectric material is air.

10. The PIFA of claim 1, wherein the dielectric material is epoxy/glass.

10

11. The PIFA of claim 1, wherein the dielectric material is alumina.

12. The PIFA of claim 1, wherein the dielectric
15 material is quartz.

13. The PIFA of claim 1, wherein the dielectric material is polytetra fluoroethylene.

20 14. The PIFA of claim 1 tuned at an operating frequency f_0 and providing a class-F load impedance.

15. The PIFA of claim 1 tuned at an operating frequency f_0 and providing an inverse class-F load impedance.
25

16. The PIFA of claim 2 wherein the transmission line is connected to a power amplifier.

17. The PIFA of claim 16, wherein the power amplifier
30 is a broadband power amplifier.

18. A method of tuning a planar inverted-F antenna (PIFA) to operate at an operating frequency f_0 and to provide

a class-F impedance, the PIFA having a top plate, a ground plane, a feed pin, a transmission line connected to the feed pin, a first shorting pin and a second shorting pin, the shorting pins connecting the top plate to the ground plane,

5 the method comprising the steps of:

a) varying the position of the top plate to locate the feed pin at or near the center of the top plate;

b) varying the distance ρ between the first and second shorting pins and the feed pin, thereby changing the
10 real part of the input impedance of the PIFA;

c) varying the height of the top plate above the ground plane to change the real part of the input impedance of the PIFA, while respectively changing the imaginary part of the input impedance of the PIFA; and

15 d) adjusting the length of the transmission line to fine tune the input impedance of the PIFA at f_0 and to maintain the desired harmonic loading at the second and third harmonics of f_0 .

20 19. A method of tuning a planar inverted-F antenna (PIFA) to operate at an operating frequency f_0 and to provide a inverse class-F impedance, the PIFA having a top plate, a ground plane, a feed pin, a transmission line connected to the feed pin, a first shorting pin and a second shorting
25 pin, the shorting pins connecting the top plate to the ground plane, the method comprising the steps of:

a) varying the top plate position so that the feed pin is a maximal distance away from the center of the top plate;

30 b) varying the distance ρ between the first and second shorting pins and the feed pin thereby changing the real part of the input impedance of the PIFA;

c) varying the height of the top plate above the ground plane to change the real part of the input impedance of the PIFA, while respectively changing the imaginary part of the input impedance of the PIFA; and

5 d) adjusting the length of the transmission line to fine tune the input impedance of the PIFA at f_0 and to maintain the desired harmonic loading at the second and third harmonics of f_0 .

10 20. A method of tuning a planar inverted-F antenna (PIFA) from a first operating frequency f_0 to a second operating frequency f_1 , the PIFA having a top plate, a ground plane, a feed pin, a transmission line connected to the feed pin, a first shorting pin and a second shorting pin, the
15 shorting pins connecting the top plate to the ground plane, the method comprising the steps of:

a) scaling the height of the top plate above the ground plane by a factor of f_0/f_1 ;

b) scaling ρ by a factor of f_0/f_1 ;

20 c) scaling the area of the top plate by a factor of $(f_0/f_1)^2$; and

d) scaling the length of the transmission line by a factor of f_0/f_1 .

25 21. A planar inverted-F antenna (PIFA) comprising of:
a rectangular top-plate, having a dimension L and a dimension W, a ground plane having dimensions larger than those of the top-plate, and a dielectric material between the top-plate and ground plane;

30 a feed pin connected to the top-plate somewhere within the top-plate's interior area of the top-plate;

22

a first shorting pin and a second shorting pin connected between, and to, the top-plate and ground plane, such that the feed pin and two shorting pins form substantially a right angle whose edges are substantially perpendicular and parallel to an edge of the top-plate, and
5 such that each shorting pin is a distance ρ from the feed pin; and

a length of transmission line connected to the end of the feed pin that is not connected to the top-plate.

10

22. A communication device comprising:

a planar inverted-F antenna (PIFA) having a top plate, a ground plane, and a feed pin connected to the top plate, a first shorting pin and a second shorting pin, the
15 first and second shorting pins connecting the top plate to the ground plane;

a power amplifier; and

a transmission line connecting the feed pin to the power amplifier.

20

23. An offset top loaded monopole (TLM) comprising:

a top plate, a ground plane, a dielectric material between the top plate and the ground plane and a feed pin connected to the top plate substantially offset from the
25 centre of the top plate to provide a desired impedance of the offset TLM at the feed pin.

24. The offset TLM of claim 23, wherein the feed pin is connected to a transmission line, the transmission line
30 being used for fine-tuning of the offset TLM.

25. The offset TLM of claim 24, wherein the transmission line is connected to a power amplifier.

26. The offset TLM of claim 23 wherein a power
5 amplifier is connected to the feed pin.

27. The offset TLM of claim 25, wherein the power amplifier is a broadband power amplifier.

10 28. The offset TLM of claim 23, wherein the dielectric material is air.

29. The offset TLM of claim 23, wherein the dielectric material is epoxy/glass.

15

30. The offset TLM of claim 23, wherein the dielectric material is alumina.

31. The offset TLM of claim 23, wherein the dielectric
20 material is quartz.

32. The offset TLM of claim 23, wherein the dielectric material is polytetra fluoroethylene.

25 33. The offset TLM of claim 23 tuned at an operating frequency f_0 and providing an inverse class-F load impedance.

34. The offset TLM of claim 24 wherein the transmission line is connected to a power amplifier.

30

35. The offset TLM of claim 34, wherein the power amplifier is a broadband power amplifier.

36. A method of tuning an offset top loaded monopole (TLM) to operate at an operating frequency f_0 and to provide a inverse class-F impedance, the offset TLM having a top plate, a ground plane, a feed pin, a transmission line
5 connected to the feed pin, the method comprising the steps of:

- a) varying the top plate position so that the feed pin is a maximal distance away from the center of the top plate;
- 10 b) varying the height of the top plate above the ground plane to change the real part of the input impedance of the offset TLM, while respectively changing the imaginary part of the input impedance of the offset TLM; and
- c) adjusting the length of the transmission line
15 to fine tune the input impedance of the offset TLM at f_0 and to maintain the desired harmonic loading at the second and third harmonics of f_0 .

37. A method of tuning an offset top loaded monopole
20 (TLM) from a first operating frequency f_0 to a second operating frequency f_1 , the offset TLM having a top plate, a ground plane, a feed pin, a transmission line connected to the feed pin, the method comprising the steps of:

- a) scaling the height of the top plate above the
25 ground plane by a factor of f_0/f_1 ;
- b) scaling the area of the top plate by a factor of $(f_0/f_1)^2$; and
- c) scaling the length of the transmission line by a factor of f_0/f_1 .

30

38. An offset top loaded monopole (TLM) comprising of:
a rectangular top-plate, having a dimension L and a dimension W, a ground plane having dimensions larger than

25

those of the top-plate, and a dielectric material sandwiched between the top-plate and ground plane;

a feed pin connected to the top-plate somewhere within the top-plate's interior area of the top-plate;

5 a length of transmission line connected to the end of the feed pin that is not connected to the top-plate.

39. A communication device comprising:

10 An offset top loaded monopole having a top plate, a ground plane, and a feed pin connected to the top plate; a power amplifier; and a transmission line connecting the feed pin to the power amplifier.

107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200